



## Predefined MIDI Map

Version: MADRIX 5.4.



M-AUDIO Code 25



▪ Please choose Preset "GNMIDI", PAD Octave must be set to "0" and work with RED illuminated Encoder Mode.

[1] Main Output Strobe Activate (Pitch Down)
[2] KEY Octave DOWN
[3] KEY Octave UP
[4] Main Output Master
[5] Audio Output Value
[6] Audio Input Value
[7] Speedmaster Deck A
[8] Speedmaster Deck B
[9] Blackout
[10] Mute Audio Output
[11] Mute Audio Input
[12] Speedmaster Deck A PAUSE
[13] Speedmaster Deck B PAUSE
[14] Group Preset 1
[15] Group Preset 2
[16] Group Preset 3
[17] Group Preset 4
[18] Group Preset 5

[19] Group Preset 6	
[20] Group Preset 7	
[21] Group Preset 8	
[22] Group Preset 9	
[23] Group Preset 10	
[24] Group Preset 11	
[25] Group Preset 12	
[26] Group Preset 13	
[27] Group Preset 14	
[28] Group Preset 15	
[29] Group Preset 16	
KEY Octave	Storage Place
- 4	[32] – [54] Storage Place Deck A 1 – 25
- 3	[32] – [54] Storage Place Deck A 13 – 37
- 2	[32] – [54] Storage Place Deck A 25 – 49
- 1	[32] – [53] Storage Place Deck A 37 – 60
0	[32] – [41] Storage Place Deck A 49 – 60
0	[42] – [54] Storage Place Deck B 1 – 13
+1	[32] – [54] Storage Place Deck B 1 – 24
+2	[32] – [54] Storage Place Deck B 13 – 36
+3	[32] – [54] Storage Place Deck B 24 – 48
+4	[32] – [54] Storage Place Deck B 36 – 60